


Practicing the advantage of a new permanent magnet motor technology

450-1350 HP






# LPMR PERMANENT MAGNET MOTOR & GENERATOR FAMILY - TECHNICAL DATA

Flange = 780x780mm Nnom = 1800 RPM Nmax = 3000/4000 RPM Mch Prt IP23&IP54

Isolat Class = H Thrm.Class = F fnom = 90 Hz fmax = 200 Hz Twtin =  $25^{\circ}$  C Qwtmin = 4m<sup>3</sup>/hPwtmax = 5 bar  $\cos (0 = 0.85 - 0.99)$ 



	Motor Type Ups = 400/460 Vrms	Pnom [KW]	Pnom [HP]	To [Nm]	Tnsp [Nm]	Effc [%]	Nbase [RPM]		Lovall [mm]	Wght [Kg]
	LPMR-350.6.07AW	350	469	2034	1858	96,2	4000	4000	1164	733
	LPMR-400.6.08AW	400	536	2346	2123	96,3	4000	4000	1200	832
	LPMR-450.6.09AW	450	603	2620	2389	96,3	4000	4000	1236	931
	LPMR-500.6.10AW	500	671	2975	2654	96,5	3800	4000	1272	1030
	LPMR-550.6.11AW	550	738	3210	2919	96,6	3450	4000	1308	1129
	LPMR-600.6.12AW	600	805	3520	3185	96,8	3130	4000	1344	1228
	LPMR-650.6.13AW	650	872	3735	3450	96,5	2900	4000	1380	1327
	LPMR-700.6.14AW	700	939	4130	3715	96,7	2700	3000	1416	1426
	LPMR-750.6.15AW	750	1006	4323	3981	96,8	2500	3000	1452	1525
	LPMR-800.6.16AW	800	1073	4713	4246	96,7	2350	3000	1488	1624
	LPMR-850.6.17AW	850	1140	4987	4512	96,9	2200	3000	1524	1723
	LPMR-900.6.18AW	900	1207	5212	4777	96,9	2100	3000	1560	1822
	LPMR-950.6.19AW	950	1274	5441	5042	96,8	2000	3000	1596	1921
	LPMR-1000.6.20AW	1000	1341	5823	5308	96,7	1900	3000	1632	2020
	Motor Type Ups = 550/690 Vrms	Pnom [KW]	Pnom [HP]	To [Nm]	Tnsp [Nm]	Effc [%]	Nbase [RPM]	Nmax [RPM]	Lovall [mm]	Wght [Kg]
Г						[%]			[mm]	-
	Ups = 550/690 Vrms	[KW]	[HP]	[Nm]	[Nm]		[RPM]	[RPM]		[Kg]
	Ups = 550/690 Vrms LPMR-350.6.07BW	[KW]	[HP] 469	[Nm] 2034	[Nm] 1858	[%] 96,3	[RPM] 4000	[RPM] 4000	[mm] 1164	[Kg]
	Ups = 550/690 Vrms LPMR-350.6.07BW LPMR-400.6.08BW	350 400	[HP] 469 536	[Nm] 2034 2346	[Nm] 1858 2123	[%] 96,3 96,5	[RPM] 4000 3850	[RPM] 4000 4000	[mm] 1164 1200	735 833
	Ups = 550/690 Vrms  LPMR-350.6.07BW  LPMR-400.6.08BW  LPMR-450.6.09BW	350 400 450	[HP] 469 536 603	2034 2346 2620	[Nm] 1858 2123 2389	[%] 96,3 96,5 96,5	[RPM] 4000 3850 3400	[RPM] 4000 4000 4000	[mm] 1164 1200 1236	735 833 932
	Ups = 550/690 Vrms  LPMR-350.6.07BW  LPMR-400.6.08BW  LPMR-450.6.09BW  LPMR-500.6.10BW	350 400 450 500	(HP) 469 536 603 671	[Nm] 2034 2346 2620 2975	[Nm] 1858 2123 2389 2654	96,3 96,5 96,5 96,6	[RPM] 4000 3850 3400 3050	[RPM] 4000 4000 4000 4000	[mm] 1164 1200 1236 1272	735 833 932 1035
	Ups = 550/690 Vrms  LPMR-350.6.07BW  LPMR-400.6.08BW  LPMR-450.6.09BW  LPMR-500.6.10BW  LPMR-550.6.11BW	350 400 450 500 550	(HP) 469 536 603 671 738	2034 2346 2620 2975 3210	[Nm] 1858 2123 2389 2654 2919	96,3 96,5 96,5 96,6 96,6	[RPM] 4000 3850 3400 3050 2800	[RPM] 4000 4000 4000 4000 4000	[mm] 1164 1200 1236 1272 1308	735 833 932 1035 1130
	Ups = 550/690 Vrms  LPMR-350.6.07BW  LPMR-400.6.08BW  LPMR-450.6.09BW  LPMR-500.6.10BW  LPMR-550.6.11BW  LPMR-600.6.12BW	350 400 450 500 550 600	[HP] 469 536 603 671 738 805	2034 2346 2620 2975 3210 3520	[Nm]  1858 2123 2389 2654 2919 3185	96,3 96,5 96,5 96,6 96,6 96,9	[RPM] 4000 3850 3400 3050 2800 2550	[RPM] 4000 4000 4000 4000 4000 4000	[mm]  1164 1200 1236 1272 1308 1344	735 833 932 1035 1130 1231
	Ups = 550/690 Vrms  LPMR-350.6.07BW  LPMR-400.6.08BW  LPMR-450.6.09BW  LPMR-500.6.10BW  LPMR-550.6.11BW  LPMR-600.6.12BW  LPMR-650.6.13BW  LPMR-700.6.14BW  LPMR-750.6.15BW	350 400 450 500 550 600 650	[HP]  469 536 603 671 738 805 872	2034 2346 2620 2975 3210 3520 3735	1858 2123 2389 2654 2919 3185 3450	96,3 96,5 96,5 96,6 96,6 96,9 96,6	[RPM] 4000 3850 3400 3050 2800 2550 2360	[RPM] 4000 4000 4000 4000 4000 4000 4000	[mm] 1164 1200 1236 1272 1308 1344 1380	735 833 932 1035 1130 1231 1332
	Ups = 550/690 Vrms  LPMR-350.6.07BW  LPMR-400.6.08BW  LPMR-450.6.09BW  LPMR-500.6.10BW  LPMR-550.6.11BW  LPMR-600.6.12BW  LPMR-650.6.13BW  LPMR-700.6.14BW	350 400 450 500 550 600 650 700	[HP] 469 536 603 671 738 805 872 939	2034 2346 2620 2975 3210 3520 3735 4130	[Nm]  1858 2123 2389 2654 2919 3185 3450 3715 3981 4246	96,3 96,5 96,5 96,6 96,6 96,9 96,6 96,9 96,8 96,9	[RPM] 4000 3850 3400 3050 2800 2550 2360 2200	4000 4000 4000 4000 4000 4000 4000 400	[mm]  1164 1200 1236 1272 1308 1344 1380 1416	735 833 932 1035 1130 1231 1332 1428
	Ups = 550/690 Vrms  LPMR-350.6.07BW  LPMR-400.6.08BW  LPMR-450.6.09BW  LPMR-500.6.10BW  LPMR-550.6.11BW  LPMR-600.6.12BW  LPMR-650.6.13BW  LPMR-700.6.14BW  LPMR-750.6.15BW	350 400 450 500 550 600 650 700 750	[HP] 469 536 603 671 738 805 872 939 1006	2034 2346 2620 2975 3210 3520 3735 4130 4323	[Nm]  1858 2123 2389 2654 2919 3185 3450 3715 3981	96,3 96,5 96,5 96,6 96,6 96,9 96,6 96,9	[RPM] 4000 3850 3400 3050 2800 2550 2360 2200 2050	[RPM] 4000 4000 4000 4000 4000 4000 4000 3000 3000	[mm]  1164 1200 1236 1272 1308 1344 1380 1416 1452	735 833 932 1035 1130 1231 1332 1428 1529
	Ups = 550/690 Vrms  LPMR-350.6.07BW  LPMR-400.6.08BW  LPMR-450.6.09BW  LPMR-550.6.11BW  LPMR-600.6.12BW  LPMR-650.6.13BW  LPMR-700.6.14BW  LPMR-750.6.15BW  LPMR-800.6.16BW	350 400 450 500 550 600 650 700 750 800	[HP]  469 536 603 671 738 805 872 939 1006 1073	[Nm]  2034 2346 2620 2975 3210 3520 3735 4130 4323 4713	[Nm]  1858 2123 2389 2654 2919 3185 3450 3715 3981 4246	96,3 96,5 96,5 96,6 96,6 96,9 96,8 96,9 96,8 97,0	[RPM] 4000 3850 3400 3050 2800 2550 2360 2200 2050 1920	[RPM] 4000 4000 4000 4000 4000 4000 3000 300	[mm]  1164 1200 1236 1272 1308 1344 1380 1416 1452 1488	[Kg]  735 833 932 1035 1130 1231 1332 1428 1529 1627
	Ups = 550/690 Vrms  LPMR-350.6.07BW  LPMR-400.6.08BW  LPMR-450.6.10BW  LPMR-550.6.11BW  LPMR-600.6.12BW  LPMR-650.6.13BW  LPMR-700.6.14BW  LPMR-750.6.15BW  LPMR-800.6.16BW  LPMR-850.6.17BW	350 400 450 500 550 600 650 700 750 800 850	[HP]  469 536 603 671 738 805 872 939 1006 1073 1140	[Nm]  2034 2346 2620 2975 3210 3520 3735 4130 4323 4713 4987	[Nm]  1858 2123 2389 2654 2919 3185 3450 3715 3981 4246 4512	96,3 96,5 96,5 96,6 96,6 96,9 96,6 96,9 96,8	[RPM] 4000 3850 3400 3050 2800 2550 2360 2200 2050 1920 1800	[RPM] 4000 4000 4000 4000 4000 4000 4000 3000 3000 3000 3000	[mm]  1164 1200 1236 1272 1308 1344 1380 1416 1452 1488 1524	[Kg]  735 833 932 1035 1130 1231 1332 1428 1529 1627 1725

- · Rotor position feedback resolver sensor built in
- All motors are water cooled forced ventilation cooling system on request
  All motors can operate in 40°C ambient temperature with different tech specification
- · Motors can be supplied in a frameless OEM version We retain the right to change any data without prior notice.



### FEATURES |

- · Embedded Permanent Magnet Segments
- Mechanical, chemical & magnetic PM protection.
- · PM rotor robust on direct motor terminals short circuit
- Constant torque & constant power control features
- · Very low torque ripple
- · Low vibration
- · High efficiency
- · High W/Kg ratio
- · Ambient friendly machine
- · Efficient water cooling system
- · Low thermal dissipation
- Low operating temperature
- · Long life

#### PRACTICE |

- · PM & reluctance torque motor contribution
- · All winding wire connections outside the machine
- · 3x3 phase system wiring
- 1x3 or 3x3 phase system supply
- · Double bearing isolation system
- · Three or nine phases connection
- · Closed mechanical design
- · Robust mechanical construction
- · Water or Air cooling system
- · Perfectly fits submersed applications
- · Frame or frameless delivery
- · No maintenance required

Energy Saving & Maintenance Free LPMR motor family join synchro reluctance and permanent magnet torque production to deliver high KW/cm3 features and to extend the constant power speed range capability. High overcurrent capability and low rotor inertia makes these motors highly dynamic. These motors have very high efficiency and low torque ripple. Stator only dissipation facilitates minimizing the cooling system.

#### BENEFITS |


- Smaller dimensions
- Lower weight
- Lower cost
- Smoother running
- Constant torque across RPM's
- Short circuit on the motor terminal support
- Mechanically protected PM segments
- Chemically protected PM segments
  - Nickel Plated
  - Resin Barrier
- Both bearings isolated
- Higher efficiency under various conditions

## APPLICATIONS

- Shipbuilding
- · Marine propeller and jet propulsion
- · Wind turbines
- · Electric vehicles traction
- · Mining and drilling
- Oil industry
- · Cement and sugar milling
- · Paper industry
- · Steel and plastic industry
- · Water pumps
- Compressors

Rotor dissipation absence makes these motors extremely efficient in a very extended speed and power range.

Heat fluxes drained through the rotor and stator for different external convection values rotor stator 22000 20000 18000 16000 14000 PM motor is suitable 12000 for stator only 10000 water cooling 8000 4000 2000 (W) o 500 1000 1500 (W/K m2)




High quality winding, advance isolation technology and no wire connections inside the motor makes these machines highly reliable and inverter compliant.

LPMR motors can be supplied over single three phase or triple three phase inverters -this way combining low power drive and redundant supply for high demanding applications



Three separate winding groups




PM segments embedded inside the rotor structure



No wire connections inside the machine

Specific design makes LPMR motors very efficient and easy to cool, producing a high torque with low operation temperature and compact construction.

The BEMF is of a pure sinusoidal waveform that enables LPMR motors for a very smooth running generating low vibration and torque ripple.



Connection box is accessible from three sides making multiple wiring supply easy and comfortable.


Solid rotor enables reliable motor high speed operation. Every PM segment is mechanically and chemically protected.



Efficient cooling system & low losses reduce LPMR motors overall dimensions



TEMA LPMR



Closed cooling system and robust mechanical design

Special rotor design allows extended motor control in Constant Power speed range